



Transistor and Thyristor (SCR) Replacement for 1336 PLUS, PLUS II, FORCE, IMPACT and REGEN Drives.

Description

These instructions cover the proper method of replacing transistor and SCR modules in the 1336 family of drives. Failure to properly prepare the mounting surface or to torque the components to rated specifications will result in decreased service life of the replacement components.

Contents

<u>Description</u>	<u>Page</u>
Safety Precautions	1
Surface Preparation	2
Installation	2
Thermal Grease Requirements	3
Torque Mounting Sequence	4
Torque Specifications	5

Safety Precautions



ATTENTION: Some printed circuit boards and drive components may contain hazardous voltage levels. Remove and lock out power before you disconnect or reconnect wires, and before you remove or replace fuses and circuit boards. Verify bus voltage by measuring the voltage between +DC and - DC on Terminal Block TB1. Do Not attempt to service the drive until the bus voltage has discharged to zero volts.



ATTENTION: Potentially fatal voltages may result from improper useage of oscilloscope and other test equipment. The oscillscope chassis may be at a potentially fatal voltage if not properly grounded. If an oscilloscope is used to measure high voltage waveforms, use only a dual channel oscilloscope in the differential mode with X100 probes. It is recommended that the oscilloscope be used in the A minus B Quasi-differential mode with the oscillscope chassis correctly grounded to an earth ground.



ATTENTION: This assembly contains parts and sub-assemblies that are sensitive to electrostatic discharge. Static control precautions are required when servicing this assembly. Component damage may result if you ignore electrostatic discharge control procedures. If you are not familiar with static control procedures, reference Allen-Bradley Publication 8000-4.5.2 Guarding Against Electrostatic Damage, or any other applicable ESD protection handbook.

Surface Preparation

After removing the transistor or SCR modules from the drive, the heat-sink and replacement modules must be prepared using the following method to ensure proper heat transfer and operation of the replacement components.

1. Remove all old heat transfer compound from the surface of the heatsink using a tool such as a rubber spatula that will not mar the heatsink surface. Remove any remaining residue with a soft cotton cloth and a cleaning fluid such as Essex Cleaning Fluid, Brownell OS-3 by Dow Corning Co. (Mineral spirits may also be used if Essex cleaning fluid is not available).
2. Use a non-marring cleaning pad such as a Scotchbrite by 3M™ to remove any oxidation from the face of the heatsink. DO NOT use steel wool or sandpaper to clean the surface of the transistor/SCR baseplate or the heatsink, as they could scratch or score the surface which will impede heat transfer from the transistor to the heatsink.
3. Follow the oxidation removal with a final cleaning of both the heatsink and the module baseplate with cleaning fluid and the soft cloth.

NOTE: Thermal compound must be applied immediately to both surfaces as detailed in the following Installation section to prevent oxidation from reoccurring.

If a cleaning agent other than Essex by Dow Corning is used, make certain it leaves No residue on the heat transfer surfaces.

Installation

Install the transistor or SCR module to the heatsink as follows:

1. Apply a liberal coating of thermal compound (AOS 52022) to the transistor or SCR module base plate using the amount of 6 gram blister packs (part number 196261) recommended in Table 1 for your particular device.
2. Apply the thermal compound until the metal surface is no longer visible. Do not allow any foreign particles or contamination to collect on the thermal grease. The nominal thickness of the grease coating should be about 0.005 inches or 0.127 millimeters.
3. Mount the transistor or SCR module on the heatsink, pressing and rotating in a slight circular motion to better seat the transistor onto the heatsink and distribute the grease more evenly.
4. Apply slight pressure and attempt to lift the module back off the heatsink. If the module does not easily separate from the heatsink, the thermal interface is correct. If the module easily separates from the heatsink with no suction effect, this could be due to insufficient grease or foreign particles on either the module base plate or the

heatsink. Remove foreign particles and/or apply more grease and reseal the module until it is properly attached to the heatsink.

Table 1.1 Thermal Grease Requirements

Spare Part Kit Number	Transistor/Resistor Part Number	Vendor Part No.	Number of 1 gram packets
74100-818-12	22501-013-01	1MB1400NN-120	2
74100-818-13	22501-013-01	1MB1400NN-120	2
74100-818-15	22501-011-02	1MB1300NN-120	2
74100-818-16	22501-011-02	1MB1400NN-120	2
74100-828-12	22501-011-01	1MB1300NN-120	2
74100-818-14	194046-Q01	1MB1600PX-140	1
74100-818-17	194046-Q01	1MB1600PX-140	1
74100-838-05	194530-Q02	TD425N16KOF	1
74100-838-06	194530-Q02	TD425N16KOF	1
74100-838-09	22501-027-01	TD500N16KOF	1
74100-838-10	22501-027-02	TD500N14KOF	1
194972	22501-026-02	TT425N14KOF	1
74100-838-15	194530-Q01	TT425N16KOF	1
74100-838-03	194529-Q02	TD250N16KOF	1
74100-838-04	194529-Q02	TD250N16KOF	1
74100-838-07	194529-Q01	TD250N16KOF	1
74100-838-08	194529-Q01	TD250N16KOF	1
74100-838-01	194528-Q01	TT142N16KOF	1
74100-838-02	194528-Q01	TT142N16KOF	1
74100-837-15	24808-676-01	DD90N12L	1
195036	164267	T1509N12TOF	3
74100-818-18	22501-014-03	FZ800R12KF1	4
74100-818-19	22501-014-04	FZ800R16KF1	4
74100-818-20	22501-014-01	FZ1200R12KF1	8
74100-818-21	22501-014-01	FZ1200R12KF1	8
74100-818-22	22501-014-02	FZ1200R16KF1	8
74100-818-23	22501-014-02	FZ1200R16KF1	8
74100-818-25	22501-014-01	FZ1200R16KF1	4
74100-818-26	22501-014-02	FZ1200R16KF1	4
74103-172-01	22501-014-02	FZ1200R12KF1	8
74103-172-02	22501-014-02	FZ1200R16KF1	8
74100-846-01	24708-501-01	Resistor	1
74100-846-02	24708-501-03	Resistor	1
74100-846-04	24708-501-05	Resistor	1
74100-846-05	24708-501-07	Resistor	1
74100-822-03	24708-470-04	Resistor	1
74100-822-04	24708-470-03	Resistor	1
74100-822-05	24708-470-03	Resistor	1
74100-822-07	24708-470-11	Resistor	1


Note: 6 gram packet is Allen-Bradley part no.196261

- Align the transistor mounting holes with the holes in the heatsink. Insert the new screws supplied with the kit in to the holes in the heatsink (Do Not reuse screws from the old module). Temporarily screw the fasteners to a finger tight position.

Spare Allen-Bradley Parts

6. Consult the mounting screw tightening sequence for your particular module as shown in Figure 1-1. Temporarily torque the mounting screws to 10% of the final torque number shown in Table 1-2.
7. Perform the final torquing of the screws in the rotation sequence shown in Figure 1-1. All screws should be at the final rated torque shown in Table 1-2.


Two Point Mounting



Temporary Torque Sequence ① → ②

Final Torque Sequence ② → ①

Four Point Mounting



Temporary Torque Sequence ① → ② → ③ → ④

Final Torque Sequence ④ → ③ → ② → ①

Six Point Mounting



Temporary Torque Sequence ② → ⑤ → ③ → ⑥ → ① → ④

Final Torque Sequence ④ → ① → ⑥ → ③ → ⑤ → ②

8. After the rated torque has been applied to the heatsink mounting screws, wait 45 minutes and then re-torque the fasteners to the final rated torque again. The thermal grease tends to redistribute in a process called "bleeding". This process tends to decrease the mounting force the screws impose on the backplate as a function of time. The correct magnitude of force needs to be re-established after the time period has passed.
9. When the module is successfully mounted and torqued reinstall the electrical leads and torque the gate and emitter lead connections to the values shown in Table 1-2.

Table 1.2 Torque Requirements

Spare Part Kit Number	Transistor/Resistor Part Number	Vendor Part No.	Base Plate Screw Torque	Power Connection Torque	Gate/Emitter Connection Torque
74100-818-12	22501-013-01	1MB1400NN-120	26 lb-in	14 lb-in	14 lb-in
74100-818-13	22501-013-01	1MB1400NN-120	26 lb-in	14 lb-in	14 lb-in
74100-818-15	22501-011-02	1MB1300NN-120	26 lb-in	14 lb-in	14 lb-in
74100-818-16	22501-011-02	1MB1400NN-120	26 lb-in	14 lb-in	14 lb-in
74100-828-12	22501-011-01	1MB1300NN-120	26 lb-in	14 lb-in	14 lb-in
74100-818-14	194046-Q01	1MB1600PX-140	26 lb-in	72 lb-in	14 lb-in
74100-818-17	194046-Q01	1MB1600PX-140	26 lb-in	102 lb-in	N/A
74100-838-05	194530-Q02	TD425N16KOF	50 lb-in	102 lb-in	N/A
74100-838-06	194530-Q02	TD425N16KOF	50 lb-in	102 lb-in	N/A
74100-838-09	22501-027-01	TD500N16KOF	50 lb-in	102 lb-in	N/A
74100-838-10	22501-027-02	TD500N14KOF	50 lb-in	102 lb-in	N/A
194972	222501-027-02	TT425N14KOF	50 lb-in	102 lb-in	N/A
74100-838-15	194530-Q01	TT425N16KOF	50 lb-in	102 lb-in	N/A
74100-838-03	194529-Q02	TD250N16KOF	50 lb-in	80 lb-in	N/A
74100-838-04	194529-Q02	TD250N16KOF	50 lb-in	80 lb-in	N/A
74100-838-07	194529-Q01	TD250N16KOF	50 lb-in	80 lb-in	N/A
74100-838-08	194529-Q01	TD250N16KOF	50 lb-in	80 lb-in	N/A
74100-838-01	194528-Q01	TT142N16KOF	50 lb-in	40 lb-in	N/A
74100-838-02	194528-Q01	TT142N16KOF	50 lb-in	40 lb-in	N/A
74100-837-15	24808-676-01	DD90N12L	50 lb-in	40 lb-in	N/A
195036	164267	T1509N12TOF	26 lb-in	208 lb-in	N/A
74100-818-18	22501-014-03	FZ800R12KF1	32 lb-in	80 lb-in	14 lb-in
74100-818-19	22501-014-04	FZ800R16KF1	32 lb-in	80 lb-in	14 lb-in
74100-818-20	22501-014-01	FZ1200R12KF1	32 lb-in	80 lb-in	14 lb-in
74100-818-21	22501-014-01	FZ1200R12KF1	32 lb-in	80 lb-in	14 lb-in
74100-818-22	22501-014-02	FZ1200R16KF1	32 lb-in	80 lb-in	14 lb-in
74100-818-23	22501-014-02	FZ1200R16KF1	32 lb-in	80 lb-in	14 lb-in
74100-818-26	22501-014-02	FZ1200R16KF1	32 lb-in	80 lb-in	14 lb-in
74103-172-01	22501-014-01	FZ1200R12KF1	32 lb-in	80 lb-in	14 lb-in
74103-172-02	22501-014-02	FZ1200R16KF1	32 lb-in	80 lb-in	14 lb-in
74100-846-01	24708-501-01	Resistor	26 lb-in	NA	N/A
74100-846-02	24708-501-03	Resistor	26 lb-in	NA	N/A
74100-846-04	24708-501-05	Resistor	26 lb-in	NA	N/A
74100-846-05	24708-501-07	Resistor	26 lb-in	NA	N/A
74100-822-03	24708-470-04	Resistor	26 lb-in	NA	N/A
74100-822-04	24708-470-03	Resistor	26 lb-in	NA	N/A
74100-822-05	24708-470-03	Resistor	26 lb-in	NA	N/A
74100-822-07	24708-470-11	Resistor	26 lb-in	NA	N/A

Spare Allen-Bradley Parts

Reach us now at www.rockwellautomation.com

Wherever you need us, Rockwell Automation brings together leading brands in industrial automation including Allen-Bradley controls, Reliance Electric power transmission products, Dodge mechanical power transmission components, and Rockwell Software. Rockwell Automation's unique, flexible approach to helping customers achieve a competitive advantage is supported by thousands of authorized partners, distributors and system integrators around the world.

Americas Headquarters, 1201 South Second Street, Milwaukee, WI 53201-2486, USA, Tel: (1) 414 382 2000, Fax: (1) 414 382 4444
European Headquarters SIMN, Boulevard du Souverain 35, 1170 Brussels, Belgium, Tel: (32) 2 6 63 0600, Fax: (32) 2 6 63 0640
Asia Pacific Headquarters, 27F Citicorp Centre, 18 Whitfield Road, Causeway Bay, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1848

