



# ProcessLogix R500.1 Control Builder Update 1

## Installation

### Before You Begin

Before beginning the installation, you must download the following files to your ProcessLogix™ Server(s):

- 500.1\_CB\_1.exe

The following software components must be installed before you install this update:

- Windows® 2000 Service Pack 2 or 3
- Internet Explorer® v6.0
- ProcessLogix R500.1

### Server Installation

You must complete this procedure on all Servers in your ProcessLogix system. If you have a redundant Server pair, you must complete the following procedure on SERVERB first, then repeat the procedure for SERVERA. Be certain that SERVERA is the Primary Server before beginning the installation.

1. Close all running applications.
2. Click **Start** ⇒ **Programs** ⇒ **ProcessLogix Server** ⇒ **Start-Stop ProcessLogix Server** to call up the ProcessLogix Server dialog box.
  - a. With the Full Mode version of the dialog box active, click the **Database Unloaded** option.
  - b. Click **Yes** to confirm the action and wait for the Server to change its state.
  - c. Close the ProcessLogix Server dialog box.
3. Using Windows Explorer, browse to the directory where the update was downloaded, double-click **500.1\_CB\_1.exe** and click **OK**.
4. Click **Setup**.

AB PLCs

5. At the Installation Complete window, click **OK**.
6. Restart the PC.
7. Logon to the system as ps\_user.  
  
If you have a non-redundant Server, the Update is complete.  
If you have a redundant Server pair, continue with Step 8.
8. On SERVERA, click **Start ⇒Programs ⇒ProcessLogix Server ⇒Station**.
9. Click **View ⇒System Status ⇒Server Redundancy**.
10. Once the Backup Server Running LED turns green, click the **Oper** field in the lower right corner of the display.
11. Enter >mngr< in the Station Logon dialog box and click **OK**.
12. Click **Synchronize**.
13. At the Synchronize databases (y/n) prompt, enter >y< and press <Enter>.

Depending on your configuration, this may take some time to complete.

14. Once the Synchronization Complete prompt appears, verify that the display shows simulated Green LED indications for the following states:

LED(s)	State(s)
Primary Server	Running
Backup Server	Synchronized Running
Link Status	Link 0 (LNK00) - OK Active link Link 1 (LNK01) - OK (Only applies if you are using a dual LAN)

15. Click **Manual Failover**.
16. At the Failover to Backup (y/n) prompt, type >y< in the entry field above the display and press <Enter>.
17. Click **Station ⇒Exit**.
18. Click **Yes** to exit Station.
19. Repeat steps 1-17 on SERVERA.

20. After completing steps 1-17 on both SERVERA and SERVERB, verify that SERVERA is now Primary and synchronize the Servers.

ProcessLogix is a trademark of Rockwell Automation.

Internet Explorer is a copyright of Microsoft Corporation.

Windows is a registered trademark of Microsoft Corporation.

**[www.rockwellautomation.com](http://www.rockwellautomation.com)**

**Corporate Headquarters**

Rockwell Automation, 777 East Wisconsin Avenue, Suite 1400, Milwaukee, WI, 53202-5302 USA, Tel: (1) 414.212.5200, Fax: (1) 414.212.5201

**Headquarters for Allen-Bradley Products, Rockwell Software Products and Global Manufacturing Solutions**

Americas: Rockwell Automation, 1201 South Second Street, Milwaukee, WI 53204-2496 USA, Tel: (1) 414.382.2000, Fax: (1) 414.382.4444

Europe: Rockwell Automation SA/NV, Vorstlaan/Boulevard du Souverain 36-BP 3A/B, 1170 Brussels, Belgium, Tel: (32) 2 663 0600, Fax: (32) 2 663 0640

Asia Pacific: Rockwell Automation, 27/F Citicorp Centre, 18 Whitfield Road, Causeway Bay, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1846

**Headquarters for Dodge and Reliance Electric Products**

Americas: Rockwell Automation, 6040 Ponders Court, Greenville, SC 29615-4617 USA, Tel: (1) 864.297.4800, Fax: (1) 864.281.2433

Europe: Rockwell Automation, Brühlstraße 22, D-74834 Elztal-Dallau, Germany, Tel: (49) 6261 9410, Fax: (49) 6261 17741

Asia Pacific: Rockwell Automation, 55 Newton Road, #11-01/02 Revenue House, Singapore 307987, Tel: (65) 351 6723, Fax: (65) 355 1733