

AC Motor Formula

To Find Amperes when HP is known:

$$\text{Single Phase} \\ I = \frac{746 * HP}{E * Eff * PF}$$

$$\text{Two Phase - *(4 - wire)} \\ I = \frac{746 * HP}{2 * E * Eff * PF}$$

$$\text{Three Phase} \\ I = \frac{746 * HP}{1.73 * E * Eff * PF}$$

To find Amperes when KW is known:

$$\text{Single Phase} \\ I = \frac{1000 * KW}{E * PF}$$

$$\text{Two Phase - *(4 - wire)} \\ I = \frac{1000 * KW}{2 * E * PF}$$

$$\text{Three Phase} \\ I = \frac{1000 * KW}{1.73 * E * PF}$$

To find Amperes when KVA is known:

$$\text{Single Phase} \\ I = \frac{1000 * KVA}{E}$$

$$\text{Two Phase - *(4 - wire)} \\ I = \frac{1000 * KVA}{2 * E}$$

$$\text{Three Phase} \\ I = \frac{1000 * KVA}{1.73 * E}$$

To find Kilowatts Input:

$$\text{Single Phase} \\ KW = \frac{E * I * PF}{1000}$$

$$\text{Two Phase - *(4 - wire)} \\ KW = \frac{2 * E * I * PF}{1000}$$

$$\text{Three Phase} \\ KW = \frac{1.73 * E * I * PF}{1000}$$

To find Kilovolt Amperes:

$$\text{Single Phase} \\ KVA = \frac{E * I}{1000}$$

$$\text{Two Phase - *(4 - wire)} \\ KVA = \frac{2 * E * I}{1000}$$

$$\text{Three Phase} \\ KVA = \frac{1.73 * E * I}{1000}$$

To find Horsepower Output:

$$\text{Single Phase} \\ HP = \frac{E * I * Eff * PF}{746}$$

$$\text{Two Phase - *(4 - wire)} \\ HP = \frac{2 * E * I * Eff * PF}{746}$$

$$\text{Three Phase} \\ HP = \frac{1.73 * E * I * Eff * PF}{746}$$

* For two phase three wire balanced circuits, the Amperes in common conductor = 1.41 times that in either of the two.

Synchronous Speed:

$$n_s = \frac{120 * f}{P}$$

Frequency:

$$f = \frac{P * n_s}{120}$$

Number of poles:

$$P = \frac{120 * f}{n_s}$$

Relation between horsepower, torque and speed:

$$HP = \frac{T * n}{5250}$$

$$T = \frac{5250HP}{n}$$

$$n = \frac{5250HP}{T}$$

Motor Slip:

$$\% Slip = \frac{n_s - n}{n_s} * 100$$