



PowerFlex 4 Parameter Addition

Reference

PowerFlex 4 *Quick Start*, Publication 22A-QS001... and
PowerFlex 4 *User Manual*, Publication 22A-UM001...

Both publications are supplied with the drive.

New Basic Program Group Parameter

P043 [Motor OL Ret]

Related Parameter(s): P033, A090

Enables/disables the Motor Overload Retention function. When Enabled, the value held in the motor overload counter is saved at power-down and restored at power-up. A change to this parameter setting resets the counter.

Options	0	"Disabled" (Default)
	1	"Enabled"

New Modbus Function Code

Function code 16 Decimal (10 Hexadecimal) added.

Modbus Function Code (Decimal)	Command
03	Read Holding Registers
06	Preset (Write) Single Register
16	Preset (Write) Multiple Registers

